K63F003UP

cam changeover switch - 3-pole - 60° - 63 A - screw mounting



Main	
Range of product	Harmony K
Product or component type	Complete cam switch
Component name	K63
[lth] conventional free air thermal current	63 A
Mounting location	Front
Fixing mode	4 holes
Cam switch head type	With front plate 64 x 64 mm
Type of operator	Black handle
Rotary handle padlocking	Without
Presentation of legend	With metallic legend, 1 - 0 - 2 black marking
Cam switch function	Changeover switch
Return	Without
Off position	With Off position
Poles description	3P
Switching positions	Right: 0° - 60° Left: 0° - 300°
IP degree of protection	IP40 conforming to IEC 529 IP40 conforming to NF C 20-010

Complementary

CAD overall width	64 mm			
Mechanical durability	300000 cycles			
	63000 mA DC at 95 V 2 contact(s) for resistive load (T = 1 ms)			
	63000 mA DC at 70 V 3 contact(s) for resistive load (T = 50 ms)			
	63000 mA DC at 48 V 2 contact(s) for resistive load (T = 1 ms) 63000 mA DC at 70 V 3 contact(s) for inductive load (T = 50 ms)			
	63000 mA DC at 48 V 2 contact(s) for inductive load (T = 50 ms)			
	63000 mA DC at 48 V 1 contact(s) for resistive load (T = 1 ms)			
	63000 mA DC at 24 V 1 contact(s) for resistive load (T = 1 ms)			
	63000 mA DC at 24 V 1 contact(s) for inductive load (T = 50 ms)			
	63000 mA DC at 140 V 3 contact(s) for resistive load (T = 1 ms)			
	55000 mA DC at 90 V 3 contact(s) for inductive load (T = 50 ms)			
	55000 mA DC at 60 V 2 contact(s) for inductive load (T = 50 ms)			
	55000 mA DC at 30 V 1 contact(s) for inductive load (T = 50 ms)			
	30000 mA DC at 160 V 3 contact(s) for resistive load (T = 1 ms)			
	30000 mA DC at 120 V 2 contact(s) for resistive load (T = 1 ms)			
	20000 mA DC at 95 V 2 contact(s) for inductive load (T = 50 ms) 30000 mA DC at 120 V 2 contact(s) for resistive load (T = 1 ms)			
	20000 mA DC at 48 V 1 contact(s) for inductive load (T = 50 ms)			
Switching capacity in mA	20000 mA DC at 140 V 3 contact(s) for inductive load (T = 50 ms)			
Tightening torque				
Tightoning torque	2.5 N.m			
LIEUTIUAI CUTTIEUTUTT	Captive screw clamp terminals flexible, clamping capacity: 2 x 10 mm ²			
Electrical connection	Captive screw clamp terminals flexible, clamping capacity: 2 x 10 mm ²			
Positive opening	With			
Contact operation	Slow-break			
[p] .ataa iiipalaa miilataha tahaga	6 kV conforming to EC 947-1			
[Uimp] rated impulse withstand voltage	6 KV conforming to EN 947-1			
Short-circuit protection	80 A cartridge fuse, type gG			
Short-circuit current	10000 A			
[en] rated medication vertage	690 V (pollution degree 3) conforming to IEC 60947-1			
[Ui] rated insulation voltage	690 V (pollution degree 3) conforming to EN 60947-1			
Switching angle	60 °			

CAD overall height	64 mm
CAD overall depth	132 mm
Net weight	0.59 kg

Environment

Standards	EN/IEC 60947-3		
Product certifications	CULus 120 V 3 hp 1 phase		
	CULus 480 V 25 hp 3 phases		
	CULus 240 V 7.5 hp 1 phase		
	CULus 240 V 10 hp 3 phases		
Protective treatment	TC		
Ambient air temperature for operation	-2555 °C		
Ambient air temperature for storage	-4070 °C		
Overvoltage category	Class II conforming to IEC 60536		
	Class II conforming to NF C 20-030		

Packing Units

Unit Type of Package 1	PCE	
Number of Units in Package 1	1	
Package 1 Weight	486 g	
Package 1 Height	7.2 cm	
Package 1 width	7.2 cm	
Package 1 Length	13.7 cm	

Offer Sustainability

☑ REACh Declaration		
Yes		
Pro-active compliance (Product out of EU RoHS legal scope) EVEN RoHS		
Yes		
Yes		
₫Yes		
China RoHS Declaration		
The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins		

Contractual warranty


Warranty	18 months		

Product data sheet Dimensions Drawings

K63F003UP

Dimensions

Front Mounting




e $\,$ support panel thickness 0.5 to 5.5 mm / 0.02 to 0.22 in in.

а		b		С		D1	
mm	in.	mm	in.	mm	in.	mm	in.
92.8	3.65	66	2.60	64	2.52	5.4	0.21

K63F003UP

Panel Cut-Out

Front Mounting



D2		D3		G1	
mm	in.	mm	in.	mm	in.
4.5	0.18	10	0.39	48	1.89


Product data sheet Technical Description

K63F003UP

Link Positions (Factory Mounted)

Diagram for 1 to 4-pole Switches

Select the number of poles according to the product characteristics



- I1 Input 1
- I2 Input 2


Marking



Angular Position of Switch



Switching Program



- (1) 1-pole
- (2) 2-pole
- (3) 3-pole
- (4) 4-pole

Convention Used for Switching Program Representation

Contact closed

Contact closed in 2 positions and maintained between the 2 positions

Sealed assembly for auto-maintain control

Overlapping contacts

Spring return position: for a switching angle of 90°, spring return is over 30° after the last position (for a maximum of 3 simultaneous contacts).

Example:

