



Main

Range	Thorsman
Product or component type	Analog multimeter
Supply	Battery 1.5 V

Complementary

Type of setting	Manual
Function available	Handsfree operations
Protection type	Fuse
Type of measurement	Resistance: x10 Ohm/x1 kOhm Voltage DC: 12/60/120/300 V Voltage AC: 12/60/300 V Current DC: 0.6/12/600 mA
Measurement category	Category III 300 V
Relative humidity	0...85 %
Language	French Polish Hungarian
Height	140 mm
Width	75 mm
Depth	50 mm
Net weight	275 g without battery

Offer Sustainability

EU RoHS Directive	Under investigation
-------------------	---------------------

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.